

WP3DPD1BT/BD
Photodiode



DESCRIPTION

- Made with PIN silicon photodiode chips


FEATURES

- Mechanically and spectrally matched to the infrared emitting LED lamp
- Package matched with IR emitter WP3A10F3C
- Black diffused lens
- Halogen-free
- RoHS compliant


APPLICATIONS

- Infrared applied systems
- Optoelectronic switches
- Photodetector control circuits
- Sensor technology

PACKAGE DIMENSIONS



Recommended PCB Layout



Notes:
1. All dimensions are in millimeters (inches).
2. Tolerance is $\pm 0.25(0.01)$ unless otherwise noted.
3. Lead spacing is measured where the leads emerge from the package.
4. The specifications, characteristics and technical data described in the datasheet are subject to change without prior notice.

ABSOLUTE MAXIMUM RATINGS at $T_A=25^{\circ}\text{C}$

Parameter	Max.Ratings	Units
Power Dissipation	150	mW
Operating Temperature	-40 to +85	$^{\circ}\text{C}$
Storage Temperature	-40 to +85	$^{\circ}\text{C}$
Lead Solder Temperature ^[1]	260 $^{\circ}\text{C}$ For 3 Seconds	
Lead Solder Temperature ^[2]	260 $^{\circ}\text{C}$ For 5 Seconds	


Notes:
1. 2mm below package base.
2. 5mm below package base.
3. Relative humidity levels maintained between 40% and 60% in production area are recommended to avoid the build-up of static electricity – Ref JEDEC/JESD625-A and JEDEC/J-STD-033.

ELECTRICAL / OPTICAL CHARACTERISTICS at T_A=25°C


Parameter	Symbol	Min.	Typ.	Max.	Units	Test Conditions
Reverse Break down Voltage	V _{(BR)R}	33	170	-	V	I _R = 100μA H = 0mW/cm ²
Reverse Dark Current	ID _(R)	-	-	10	nA	V _R = 10V H = 0mW/cm ²
Open Circuit Voltage	V _{OC}	-	390	-	mV	λ = 940nm H = 5mW/cm ²
Rise Time	t _r	-	6	-	nS	V _R = 10V λ = 940nm R _L = 1000Ω
Fall Time	t _f	-	6	-	nS	
Light Current	I _S	0.3	1.0	-	μA	V _R = 5V E _e = 0.08mW/cm ² λ = 940nm
Total Capacitance	C _T	-	5	-	pF	V _R = 10V F = 1MHZ H = 0mW/cm ²
Range of Spectral Bandwidth	λ _{0.1}	670	-	1070	nm	-
Wavelength of Peak Sensitivity	λ _p	-	940	-	nm	-

TECHNICALDATA

RELATIVE SPECTRAL SENSITIVITY vs. WAVELENGTH




PHOTODIODE



1. Recommend pre-heat temperature of 105°C or less (as measured with a thermocouple attached to the LED pins) prior to immersion in the solder wave with a maximum solder bath temperature of 260°C.
2. Peak wave soldering temperature between 245°C - 255°C for 3 sec (5 sec max).
3. Do not apply stress to the epoxy resin while the temperature is above 85°C.
4. Fixtures should not incur stress on the component when mounting and during soldering process.
5. SAC 305 solder alloy is recommended.
6. No more than one wave soldering pass.

The diagram illustrates the packaging process in three stages:

- Stage 1:** Three individual components are shown on the left.
- Stage 2:** An arrow points to a bag containing 1,000 pieces. A label is indicated on the bag.
- Stage 3:** An arrow points to an open box containing 28K pieces, with the brand name "Kingbright" visible on the inside of the lid.
- Stage 4:** An arrow points to a closed box containing 56K pieces. The brand name "Kingbright" is prominently displayed on the front, and an "Outside Label" is indicated on the top.



PRECAUTIONS


Storage Conditions

1. Avoid continued exposure to the condensing moisture environment and keep the product away from rapid transitions in ambient temperature.
2. The LEDs should be stored at temperature $<30^{\circ}\text{C}$ and relative humidity $<70\%$. If the packaging is opened but not used within three months, the unused LEDs should be stored in a sealed container with nitrogen atmosphere and moisture absorbent material.

LED Mounting Method



1. The lead pitch of the LED must match the pitch of the mounting holes on the PCB during component placement. Lead-forming may be required to insure the lead pitch matches the hole pitch. Refer to the figure below for proper lead forming procedures.

Note 1-3: Do not route PCB trace in the contact area between the leadframe and the PCB to prevent short-circuits.



" O " Correct mounting method " X " Incorrect mounting method


2. When soldering wires to the LED, each wire joint should be separately insulated with heat-shrink tube to prevent short-circuit contact. Do not bundle both wires in one heat shrink tube to avoid pinching the LED leads. Pinching stress on the LED leads may damage the internal structures and cause failure.



3. Use stand-offs (Fig. 1) or spacers (Fig. 2) to securely position the LED above the PCB.
4. Maintain a minimum of 3mm clearance between the base of the LED lens and the first lead bend (Fig. 3, Fig. 4).
5. During lead forming, use tools or jigs to hold the leads securely so that the bending force will not be transmitted to the LED lens and its internal structures. Do not perform lead forming once the component has been mounted onto the PCB. (Fig. 5)

Lead Forming Procedures

1. Do not bend the leads more than twice. (Fig. 6)
2. During soldering, component covers and holders should leave clearance to avoid placing damaging stress on the LED during soldering. (Fig. 7)
3. The tip of the soldering iron should never touch the lens epoxy.
4. Through-hole LEDs are incompatible with reflow soldering.
5. If the LED will undergo multiple soldering passes or face other processes where the part may be subjected to intense heat, please check with Kingbright for compatibility.



PRECAUTIONARY NOTES

1. The information included in this document reflects representative usage scenarios and is intended for technical reference only.
2. The part number, type, and specifications mentioned in this document are subject to future change and improvement without notice. Before production usage customer should refer to the latest datasheet for the updated specifications.
3. When using the products referenced in this document, please make sure the product is being operated within the environmental and electrical limits specified in the datasheet. If customer usage exceeds the specified limits, Kingbright will not be responsible for any subsequent issues.
4. The information in this document applies to typical usage in consumer electronics applications. If customer's application has special reliability requirements or have life-threatening liabilities, such as automotive or medical usage, please consult with Kingbright representative for further assistance.
5. The contents and information of this document may not be reproduced or re-transmitted without permission by Kingbright.
6. All design applications should refer to Kingbright application notes available at <https://www.KingbrightUSA.com/ApplicationNotes>